

VTB-2A

bhv

World's smallest ...



...composite switcher

A compact and powerful low cost 4-input analogue composite video switcher designed for fast reliable operation in the field

- Broadcast specification with 4x4 input/output switching
- Auto/manual dissolve and wipes with auto fade to black
- Four genlock outputs and auto-detect genlock input
- Full GPI with on-board tally driver module
- Battery or AC operation
- Dual format PAL/NTSC

The VTB-2A is the world's smallest portable 4-input field switcher currently in production, and it's equally at home on shoots and in satellite trucks. Operationally, this switcher is of the conventional program/preview configuration, but has two additional switched auxiliary outputs, thus offering 4x4 routing facilities. All outputs are broadcast specification.

The features include take (cross-cut), auto/manual mix and wipe and auto fade to black. The auto functions are variable in the range 0 - 5 seconds.

The VTB-2A runs from a nominal 12V d.c. (actual 10 - 18V) via a standard XLR connector, and its low current consumption makes it ideal for battery powering; typically a BP-90 will give in excess of 12 hours continuous use. PAL/NTSC switching is installed, and the VTB-2A is shipped with a universal power supply (90-263V a.c.).



For stand-alone operation, input 1 is defined as the sync source. Other sources are genlocked via the black and burst outputs derived from input 1. There is also an external reference input, and the connection of a composite signal at this point will cause the VTB-2A to switch over automatically, allowing the user to lock the switcher to an external reference. Should the external reference fail for any reason, the switcher will revert to input 1 syncs without significant interruption to the program output.

The GPI port offers open collector tally outputs, which will operate external devices such as tally lights to a limit of 60V at 500mA. Access to triggers for the take and fade to black functions and bus selection are also available at this connector.

Communitek Video Systems
351 West 41st Street
New York, NY 10036
Tel: 212-967-1774 Fax: 212-967-1812
www.communitekvideo.com

Brick House Video Ltd.
99 Adelaide Road St. Denys
Southampton SO17 2HZ United Kingdom
Tel: +44 (0) 23 8067 6026 Fax: +44 (0) 23 8058 3426
e-mail: sales@brickhousevideo.com